Taser AXON Body 2

Axon Body 2 camera

Topics

- Axon Body 2 Overview
- Operating Functions
- Mounting
- Axon Dock 2
- Pairing the Device
- Axon View App

Axon Body 2 camera
Features

- Configurable HD Capability
- Dual Channel Audio
- Mute and Markers
- Newly Designed Mounts
- Vibrating Feedback

Axon Body 2 camera
Features

- More than 12 hours of battery life
- 30 frames per second
- 143°diagonal field of view camera lens
- 1280 x 720 HD
- 30 second Pre-event buffer
- Wi-Fi to pair your camera to the Axon application
- Haptic (status notification via device vibration)

Axon Body 2 camera
Nomenclature

Lens

On/Off Switch

Function Button

Speaker

EVENT Button

Battery LED

Microphone

Battery Status Button

Axon Body 2 camera
Nomenclature

Connection Socket

Function LED

Operation LED

Axon Body 2 camera

Operation LED	Operating Mode
Solid Red	Booting Up
Blinking Green	Buffering
Blinking Red	Recording

Axon Body 2 camera

When on the camera is in **BUFFERING mode.** 30 seconds. Green flashing LED

Axon Body 2 camera

To start recording video, double tap the **EVENT Button**. LED blinks red.

Axon Body 2 camera

To stop recording, press and hold the **EVENT Button**.

Axon Body 2 camera

Muting Audio

Function Button

Press and hold the Function Button 3 seconds to mute audio. Press another 3 seconds to re-enable the audio recording.

Axon Body 2 camera

Battery Life

Battery LED	Battery Life Indicator
Solid Green	41-100%

Axon Body 2 camera

Battery Life

Battery LED	Battery Life Indicator
Solid Green	41-100%
Solid Yellow	**20-40%**

Axon Body 2 camera

Battery Life

Battery LED	Battery Life Indicator
Solid Green	41-100%
Solid Yellow	20-40%
Solid Red	0-19%
Blinking red & Yellow	Depleted Dead Battery

Axon Body 2 camera

Camera Position P&P 6.131

- Deputies/community services officers shall wear the BWC in a position that provides for the most effective recording angle for the model provided to the wearer while also ensuring the ability to safely activate the camera prior to, or during an incident. Deputies/community service officer shall not intentionally obscure the view of their body worn camera.

Axon Body 2 camera

Mounting

Flexible Mount

Outerwear Mount

Axon Body 2 camera

Mounting

Small Pocket Mount

Axon Body 2 camera

Docking & Charging the camera

Axon Body 2 camera

Docking & Charging the camera
Operation Manual

When not in use, the BWC devices shall be stored in the designated docking module or in a secure storage location at each patrol station, court, or any detention facility. Deputies will ensure the BWC is properly seated into the docking station to allow for proper downloading and charging.

Axon Body 2 camera

Docking & Charging the camera
Operation Manual

After verifying the required metadata has been added to all recorded events, deputies shall place the BWC into a slot on the Evidence Transfer System at the end of their shift. This will allow for the battery to recharge. The data will automatically be transferred from the BWC through the Evidence Transfer System and/or Sheriff's Data Services dedicated server.

Axon Body 2 camera
Camera LED Information during uploading

Initial connection (momentary)
Solid red (for up to 20 seconds or fewer)

In queue awaiting upload Solid yellow

Uploading data Blinking yellow

Upload Complete Solid green

Axon Body 2 camera
Camera LED problems uploading

Device not assigned, agency mismatch, camera set in the offline mode, or device error Blinking red

Firmware update, internal battery charging, extremely low battery, or memory full
Blinking red and yellow

Transfer error, device re-trying to transfer or camera is left powered on when inserted
Blinking green and yellow

Network error (no connection) Blinking red, yellow, and then green (cycling all colors)

Axon Body 2 camera
Camera LED problems uploading

Axon Dock has no communication with the camera LED off

Re-seat it into the dock

Axon Body 2 camera

AXON VIEW Smart Device App setup

Axon Body 2 camera

AXON VIEW Smart Device App

Provides the following capabilities:

- Pairs Axon cameras with iOS devices
- Instant replay
- Live video streaming assists with optimal camera placement
- GPS tagging maps video evidence automatically
- Real-time metadata input enables searching and accurate retention

Axon Body 2 camera

AXON VIEW Smart Device App setup

Steps to pair BWC with App

- Turn on WiFi and Bluetooth on phone
- Turn **OFF** AXON Body 2 Camera
- Launch Axon View App from home screen

Axon Body 2 camera

Steps to pair BWC with App

Axon Body 2 camera

Steps to pair BWC with App

SDCSD.evidence.com

Click Continue

Axon Body 2 camera

Steps to pair BWC with App

Body 2

Stop! Now turn on camera wait for boot up

Axon Body 2 camera

Steps to pair BWC with App

- Press both the **Event button** and the **Function button** together for 4-5 seconds

- Press Initiate Pairing

Look at serial # on bottom

Axon Body 2 camera

Steps to pair BWC with App

- Select your camera serial #. **Double check the bottom of your camera!**

Axon Body 2 camera

Steps to pair BWC with App

- Select Continue

Axon Body 2 camera

Steps to pair BWC with App

1. Select Configure WiFi
2. Press Allow
3. Install
4. Enter Passcode
5. Install
6. Done
7. Open
8. Allow

Axon Body 2 camera

Select the (i)

Axon Body 2 camera

Axon Body 2

Volume tone

Vibration

Stealth Mode

Agency SDSD

SETTINGS

CAMERA

AXON BODY 2

VOLUME   MEDIUM

VIBRATION

STEALTH MODE

RECONFIGURE WIFI

FORGET CURRENT CAMERA

SUPPORT

CONTACT US

ACCOUNT SETTINGS

AGENCY   San Diego County SD

Axon Body 2 camera

Click the X

Axon Body 2 camera

Click the live view

San Diego County Sheriff's Department
Video Analysis Unit

Axon Body 2 camera

Steps to pair BWC with App

Click done when
finished

Axon Body 2 camera

Click top video

Axon Body 2 camera

Play video

ID CAD Incident number

Title bar LAST NAME

Categories drop menu

Click on ID

Axon Body 2 camera

CAD Incident number

Title menu Last Name

Categories drop menu

Click SAVE when done

San Diego County Sheriff's Department
Video Analysis Unit

Axon Body 2 camera

AXON VIEW Smart Device App

- **There is only a 5 frame per second live streaming bandwidth on Bluetooth.**

Axon Body 2 camera

AXON VIEW Smart Device App

The Camera Details tab includes:

- Recording status
- Remaining record time
- Battery status

What is Commander?

- Commander is a digital evidence management program

- Currently only for management of BWC videos

- Potential in the future to include all forms of digital evidence such as interview video, audio files, photographs, case documents, and BWC video

Launching Commander

- Launch Commander from Shortcut Icon on Desktop
- Commander Client Login screen appears
- Type in your Username and Password in text boxes and click **Login**
- This will be your Sheriff's Desktop username and password

Commander Main Page

Search Pane

AXON Commander

Search

123   [Go]

☐ 📂 Search only through my files

Geo-fence

Coordinates: [   ] Clear

Select from map

Time and Date

● Any time   ● Last [90] days   ● Range

Filters

● 💻 All Files   ● 📁 Folders
● 🗄 Bookmarks   ● 🗄 Cabinets
● 👥 Areas   ● 👤 Users
● 📦 Sources   ● 📑 Tags
● 🖥 Servers

Media Files

View ▼ | Sort results by ▼ | Results per page ▼

August, 2015   [3 item(s)]

	2015-08-21 12:31:50 28m9s MP4
	2015-08-21 12:31:46 30m2s MP4
	2015-08-21 12:31:42 30m2s MP4

FLEX.X78058038.0012.150821.12...   BODY.X78032315.0015.150821.1...   BODY.X78046669.0013.150821.1...

June, 2014   [3 item(s)]

	2014-06-29 00:18:40 JPG
	2014-06-29 00:18:36 JPG
	2014-06-29 00:18:18 JPG

Scene 1234   Scene 1234   Scene 1234

July, 2007   [5 item(s)]

	2007-07-11 07:13:02 JPG
	2007-07-11 07:13:02 JPG
	2007-07-11 07:13:02 JPG
	2007-07-11 07:13:02 JPG

Shooting   Shooting   Shooting   Shooting

	2007-07-11 07:13:02 JPG

Shooting

Tagging

- Any file in Commander can be tagged which allows users to classify data for easy Search
- For Patrol you will enter "Case ID", Category **NetRMS case #** (like Axon View Application metadata)
- Two types of Tags: Drop down and Value
- Tag drop down is a list of tag classifications which are preloaded and appear in a drop down selection list
- Value tags apply free-form text
- You can apply tags to multiple files at once
- You can remove and change tags as needed (will be in audit report)

Tagging

Tagging

San Diego County Sheriff's Department
Video Analysis Unit

For recommendations, comments and feedback send an email to
VAU@sdsheriff.org

For any inquires that require a response please contact a member of the VAU directly